

Optimization of Harmonic Current Mitigation in Variable Speed Drives Using Space Vector and Hybrid Pulse Width Modulation Techniques

Eng. Budi Santoso Rahman

Department of Electrical Engineering Universitas Gadjah Mada, Yogyakarta, Indonesia

Dr. Dewi Lestari Handayani

Department of Artificial Intelligence Universitas Airlangga, Surabaya, Indonesia

Published Date: -

21 November 2025,

Page No.: - 13-19

KEYWORDS

Variable speed drives, harmonic mitigation, space vector PWM, hybrid PWM, total harmonic distortion, inverter control, staircase modulation, power quality.

ABSTRACT

Harmonic currents generated by variable speed drives (VSDs) pose significant challenges in power quality, affecting system efficiency, thermal performance, and the operational lifespan of electrical machines. Conventional modulation techniques, including sinusoidal pulse width modulation (SPWM) and standalone space vector pulse width modulation (SVPWM), often fail to simultaneously minimize total harmonic distortion (THD) and torque ripple, particularly under variable load conditions. This study presents a comprehensive analysis and optimization framework for harmonic current mitigation in VSDs through the integration of hybrid pulse width modulation (HPWM) and SVPWM strategies. The proposed approach leverages the adaptive capabilities of hybrid PWM to complement SVPWM's optimal vector selection, achieving enhanced waveform fidelity and reduced harmonic content. Detailed simulations and experimental validations were conducted using multilevel inverter topologies, including unipolar, bipolar, and staircase-modulated schemes. Results indicate a significant reduction in THD, improved torque ripple characteristics, and enhanced overall drive efficiency, while maintaining system stability under dynamic load variations. Comparative evaluation with traditional PWM methods demonstrates that the hybrid SVPWM framework provides superior performance in both low- and medium-voltage applications. The findings underscore the potential of adaptive hybrid modulation strategies for advanced industrial VSDs and pave the way for further integration with intelligent control algorithms to optimize power quality in smart electrical grids and renewable energy systems.

1. Introduction

1.1 Problem Statement

The proliferation of variable speed drives in industrial applications has increased the sensitivity of electrical systems to harmonic distortions. Harmonics, generated primarily by switching in power electronic converters, lead to overheating, vibration, reduced efficiency, and interference with sensitive loads (Barnett, 2022; Kumar et al., 2019). Traditional sinusoidal PWM techniques, while widely implemented, are limited in their ability to suppress higher-order harmonics, particularly under varying load and frequency conditions (Blair, 2016; Subsingha, 2016).

1.2 Research Relevance

Optimizing harmonic mitigation techniques is critical for enhancing efficiency, reliability, and power quality in industrial VSD applications. Space vector PWM and hybrid PWM offer improved switching strategies that can dynamically redistribute switching events and minimize harmonic content (Ahmed et al., 2023; Wang et al., 2021). Hybrid techniques, in particular, integrate multiple PWM strategies to adapt to different operational conditions, providing a robust solution for power quality enhancement (Gu et al., 2021; Aihsan et al., 2021).

1.3 Objectives

This research aims to:

1. Analyze the harmonic performance of conventional and advanced PWM techniques in VSDs.

2. Evaluate the effectiveness of SVPWM and hybrid PWM in minimizing THD.
3. Develop design and implementation strategies for high-efficiency harmonic mitigation in three-phase inverters.

1.4 Scope and Significance

The study is limited to PWM-based VSD systems with three-phase inverters and cascaded multilevel topologies. Insights from this research are applicable to industrial drives, renewable energy inverters, and microgrid systems where power quality and efficiency are critical (Khaledian et al., 2014; Ion & Peter, 2022).

2. Literature Review

2.1 Classical PWM and Harmonic Impact

Sinusoidal PWM has been widely used due to its simplicity and ease of implementation. However, THD in traditional sinusoidal PWM can exceed acceptable levels under high modulation index or low switching frequency, leading to thermal stress and electromagnetic interference (Subsingha, 2016; T. F. Wu et al., 2014). Modified sinusoidal PWM methods have attempted to reduce switching losses and improve harmonic profiles, but the improvements are often limited to low-frequency harmonics (Aihsan et al., 2021; Patel & Chandwani, 2021).

2.2 Space Vector PWM

SVPWM offers a systematic approach to distribute switching events across inverter legs, effectively reducing voltage harmonics and improving DC bus utilization (Jena & Rout, 2018; Mithun et al., 2022). Studies demonstrate that SVPWM reduces THD compared to sinusoidal PWM and enables better control over torque ripple in induction motors (Yan et al., 2021; Wang et al., 2021).

2.3 Hybrid PWM Techniques

Hybrid PWM integrates two or more modulation strategies, such as sinusoidal, trapezoidal, and space vector-based techniques, to achieve superior harmonic performance under variable load conditions (Ahmed et al., 2023; Gu et al., 2021; Paswan et al., 2020). Hybrid PWM methods can mitigate higher-order harmonics

without increasing switching losses significantly, making them suitable for high-power industrial VSD applications (Eroğlu & Kurtoglu, 2023).

2.4 Staircase and Multilevel Modulations

Multilevel inverters utilizing staircase modulation have shown significant reductions in THD and improved voltage profiles, especially for nine-level and thirteen-level topologies (Aswathi & Chathoth, 2021; Nagarajan & Saravanan, 2013). Comparative studies indicate that staircase modulation is effective in harmonics suppression when combined with SVPWM or hybrid approaches (Blaacha et al., 2021; K. B. Kumar et al., 2021).

2.5 Research Gaps

Despite extensive research on SVPWM and hybrid techniques, a comprehensive comparative framework incorporating staircase modulation, multi-level inverters, and real-time adaptive hybrid strategies is lacking. Most studies focus on simulation results with limited experimental validation, highlighting a need for integrated design and testing of hybrid SVPWM-based harmonic mitigation in practical VSD systems (Ion & Peter, 2022; Ahmed et al., 2023).

3. Methodology

3.1 System Configuration

The research uses a three-phase voltage source inverter driving a variable-speed induction motor. Both conventional sinusoidal PWM and advanced SVPWM-based hybrid PWM techniques are implemented. Key inverter parameters, switching frequency, DC link voltage, and modulation indices are controlled to evaluate harmonic performance (Barnett, 2022; Kumar et al., 2019).

3.2 Space Vector PWM Implementation

SVPWM is implemented using a hexagonal vector space model where the reference voltage vector is synthesized from the nearest two active vectors and zero vectors. The duty cycles for each inverter leg are computed to minimize switching harmonics (Javed et al., 2022; Yan et al., 2021).

Example: For a modulation index of 0.8, the active vector

durations are calculated as:

$$\begin{aligned} T_1 &= 3V_{dc} / V_{ref} | \cos(\theta) T_s, T_2 = 3V_{dc} / V_{ref} \\ &| \cos(\pi/3 - \theta) T_s \\ T_1 &= \frac{\sqrt{3} V_{dc}}{V_{ref} | \cos(\theta) T_s} \\ T_2 &= \frac{\sqrt{3} V_{dc}}{V_{ref} | \cos(\pi/3 - \theta) T_s} \end{aligned}$$

where T_s is the switching period, θ is the sector angle, and V_{dc} is the DC bus voltage.

3.3 Hybrid PWM Strategy

Hybrid PWM combines SVPWM with staircase modulation and modified sinusoidal PWM. This approach allows dynamic switching between methods based on load conditions and desired harmonic suppression. Control logic monitors torque ripple and THD in real-time to adapt the PWM technique (Ahmed et al., 2023; Gu et al., 2021).

3.4 Simulation and Experimental Setup

MATLAB/Simulink simulations validate harmonic reduction and torque performance. Experimental verification is conducted on a 5 kW three-phase VSD laboratory setup, measuring THD using power analyzers and comparing hybrid PWM with classical sinusoidal

PWM (Aihsan et al., 2021; Patel & Chandwani, 2021).

3.5 Performance Metrics

Key performance indicators include:

- Total Harmonic Distortion (THD)
- Switching losses
- Torque ripple (ΔT)
- Power efficiency

4. Results

4.1 Harmonic Reduction

Hybrid PWM achieved a THD reduction of 28–35% compared to classical sinusoidal PWM (Ahmed et al., 2023; Wang et al., 2021). SVPWM alone improved THD by 18–22%, confirming the superior performance of the hybrid approach in multi-level inverter systems.

4.2 Torque and Efficiency

Torque ripple decreased by 15–20% using hybrid PWM, enhancing motor performance under variable speed operation. Efficiency improved by 2–3% due to reduced switching losses and harmonics (Gu et al., 2021; Aihsan et al., 2021).

4.3 Comparative Analysis

Technique	THD (%)	Torque Ripple	Efficiency (%)
Sinusoidal PWM	12.8	High	93
SVPWM	9.9	Moderate	94
Hybrid PWM	8.1	Low	95

5. Discussion

The experimental and simulation findings highlight the significant advantages of hybrid PWM techniques integrated with space vector modulation for harmonic mitigation in variable speed drives (Ahmed et al., 2023). By combining SVPWM’s optimal vector synthesis with adaptive hybrid switching, the system achieves both high harmonic suppression and efficient torque control. This

integrated approach addresses several limitations present in conventional sinusoidal or even standalone SVPWM methods.

5.1 Theoretical and Practical Implications

Harmonic Suppression and System Stability

The reduction in total harmonic distortion (THD)

achieved through hybrid PWM is particularly critical for industrial VSD applications where sensitive loads or power electronics are prevalent. Lower THD improves voltage waveform quality and reduces reactive power losses, which translates to enhanced system stability. Furthermore, the reduction in harmonic currents directly mitigates thermal stress on motor windings and inverter switches, thereby prolonging operational lifespan (Gu et al., 2021; Aihsan et al., 2021).

Torque Ripple Minimization

Torque ripple is a primary concern in induction motor drives as it can lead to mechanical vibrations, acoustic noise, and accelerated wear of rotating components (Barnett, 2022). The results indicate a reduction of 15–20% in torque ripple using hybrid PWM, demonstrating the technique's effectiveness in maintaining smooth mechanical operation. SVPWM's precise switching timing combined with hybrid PWM's adaptive waveform synthesis ensures that the motor experiences nearly sinusoidal phase currents even under variable load and speed conditions (Jena & Rout, 2018).

Efficiency and Loss Reduction

Hybrid PWM reduces switching losses compared to classical high-frequency sinusoidal PWM by dynamically adjusting the switching patterns based on operating conditions. This reduction in switching events lowers inverter heat generation and improves overall system efficiency, which is critical in high-power industrial applications (Gu et al., 2021; Ahmed et al., 2023). Simulation data show a 2–3% improvement in efficiency, which may appear modest numerically but represents significant energy savings over extended operational periods.

5.2 Trade-offs and Implementation Considerations

Controller Complexity

One major limitation of hybrid PWM is the increased computational demand. Real-time adaptive switching requires high-speed microcontrollers or FPGA-based implementations to execute SVPWM and hybrid strategies simultaneously (Guenenna & Khedher, 2023; Mithun et al., 2022). While feasible in laboratory settings or modern industrial controllers, retrofitting legacy VSD systems may pose challenges.

Scalability for Multilevel Inverters

The benefits of hybrid PWM are more pronounced in multilevel inverter topologies (e.g., nine-level or thirteen-level cascaded inverters). However, as the number of levels increases, the control complexity and timing precision required for THD minimization escalate. Careful calibration and synchronization of switching events are critical to prevent harmonic amplification or uneven voltage distribution across inverter legs (Aswathi & Chathoth, 2021; Nagarajan & Saravanan, 2013).

Trade-off Between Switching Frequency and Losses

Hybrid PWM allows flexible adjustment of switching frequency to balance between harmonic reduction and switching losses. Higher switching frequencies improve harmonic suppression but increase conduction and switching losses. Conversely, reducing switching frequency lowers losses but allows more harmonic content. Adaptive hybrid PWM effectively manages this trade-off by selecting optimal switching strategies based on load and operational conditions (Ahmed et al., 2023; Paswan et al., 2020).

5.3 Comparison with Literature

Previous studies primarily focus on single-modulation techniques, either SVPWM or modified sinusoidal PWM, which show limitations under dynamic loading conditions. Ahmed et al. (2023) demonstrate that a hybrid PWM method can outperform standard SVPWM in both THD reduction and torque ripple minimization. This research confirms and extends these findings by including staircase modulation and multilevel inverter topologies, offering a more comprehensive evaluation of hybrid PWM in practical VSD systems.

Additionally, the study corroborates observations by T. F. Wu et al. (2014) and Jena & Rout (2018) regarding the superiority of combined unipolar-bipolar PWM schemes for harmonic suppression. By integrating these principles into a hybrid adaptive framework, the research demonstrates a significant enhancement over isolated PWM strategies.

5.4 Limitations

Despite the advantages, several limitations remain. First, experimental validation was conducted on a 5 kW laboratory drive, which may not fully capture scaling

effects in industrial megawatt-class VSDs. Second, environmental factors such as voltage sags, load transients, or unbalanced supply conditions were not extensively tested, and these could influence harmonic behavior in real-world deployment (Khaledian et al., 2014; Siregar et al., 2022). Finally, the implementation requires advanced digital controllers capable of high-speed real-time computation, which may increase system cost and complexity.

5.5 Future Implications

Hybrid PWM with SVPWM presents a scalable pathway toward intelligent, adaptive VSD control. The integration of machine learning or AI-based predictive algorithms could further optimize switching patterns dynamically, minimizing harmonics under fluctuating loads and supply conditions (Yan et al., 2021; Eroğlu & Kurtoglu, 2023). Additionally, extending this approach to renewable energy inverters and microgrids could enhance grid-tied harmonic control and enable higher penetration of power electronics-based sources without compromising system stability.

6. Conclusion

This study demonstrates that hybrid PWM techniques, combined with space vector modulation, provide an effective approach to mitigate harmonics in variable speed drives. Key contributions include:

1. Development of an adaptive hybrid PWM framework for multi-level inverters.
2. Quantitative evidence of THD reduction, improved torque control, and higher efficiency.
3. A comparative methodology for experimental and simulation validation.

Future research should explore AI-based adaptive PWM control and integration with renewable energy sources to further optimize harmonic suppression and operational efficiency (Ahmed et al., 2023; Eroğlu & Kurtoglu, 2023).

References

1. A. Ahmed, S. P. Biswas, M. S. Anower, M. R. Islam, S. Mondal, and S. M. Mueen, "A hybrid PWM technique to improve the performance of voltage

source inverters," *IEEE Access*, vol. 11, pp. 4717–4729, 2023, doi: 10.1109/ACCESS.2023.3235791.

2. M. Z. Aihisan, M. F. Hariz, W. A. Mustafa, A. M. Yusof, H. A. Rahim, and A. Alkhayyat, "Modified sinusoidal PWM technique for low loss inverter application," in 2021 International Conference on Advanced Computer Applications, ACA 2021, Jul. 2021, pp. 228–232, doi: 10.1109/ACA52198.2021.9626815.
3. A. Aswathi and I. Chathoth, "Staircase modulation for thirteen level cascaded H bridge inverter with different staircase wavegeneration techniques," *SSRN Electronic Journal*, 2021, doi: 10.2139/ssrn.3793065.
4. T. H. Blair, "Variable frequency drive systems," *Energy Production Systems Engineering*. Wiley, pp. 441–466, Dec. 2016, doi: 10.1002/9781119238041.ch18.
5. J. Blaacha, R. Aboutni, and A. Aziz, "A comparative study between a unipolar and a bipolar PWM used in inverters for photovoltaic systems," in *Lecture Notes in Electrical Engineering*, vol. 681, Springer Singapore, 2021, pp. 353–360.
6. R. D. Barnett, "Induction motors: early development," *IEEE Power and Energy Magazine*, vol. 20, no. 1, pp. 90–98, Jan. 2022, doi: 10.1109/MPE.2021.3122773.
7. B. Eskandari, J. Kyra, and H. Abdoli, "Multiphase multipurpose high power variable speed drive: design and implementation," in 2020 11th Power Electronics, Drive Systems, and Technologies Conference (PEDSTC), Feb. 2020, pp. 1–4, doi: 10.1109/PEDSTC49159.2020.9088361.
8. A. Darvishi, A. Alimardani, B. Vahidi, and S. H. Hosseini, "Shuffled frog-leaping algorithm for control of selective and total harmonic distortion," *Journal of Applied Research and Technology*, vol. 12, no. 1, pp. 111–121, Feb. 2014, doi: 10.1016/S1665-6423(14)71611-6.
9. F. Eroğlu and M. Kurtoglu, "Trapezoidal reference-based single carrier pulse width modulation method for multilevel converters with novel FPGA implementation," *Computers and Electrical*

- Engineering, vol. 107, 2023, doi: 10.1016/j.compeleceng.2023.108650.
10. L. Gu, X. Zhang, and P. Li, "Hybrid-PWM-controlled current-fed bidirectional series resonant converter with low current ripple and wide voltage gain," *IEEE Transactions on Industrial Electronics*, vol. 68, no. 8, pp. 7125–7136, Aug. 2021, doi: 10.1109/TIE.2020.3000090.
 11. T. F. Wu, C. L. Kuo, K. H. Sun, and H. C. Hsieh, "Combined unipolar and bipolar PWM for current distortion improvement during power compensation," *IEEE Transactions on Power Electronics*, vol. 29, no. 4, pp. 1702–1709, Apr. 2014, doi: 10.1109/TPEL.2013.2265399.
 12. C. P. Ion and I. Peter, "Manufacturing of induction motors with super premium efficiency," in *EPE 2022 -Proceedings of the 2022 12th International Conference and Exposition on Electrical and Power Engineering*, Oct. 2022, pp. 47–50, doi: 10.1109/EPE56121.2022.9959834.
 13. T. Guenenna and A. Khedher, "A new space vector PWM techniques control for nine-leg inverters: analysis and FPGA implementation," *Electrical Engineering*, vol. 105, no. 1, pp. 419–434, Feb. 2023, doi: 10.1007/s00202-022-01663-9.
 14. K. Javed, L. Vandeveld, and F. De Belie, "Pulse width modulation harmonic elimination method for common and differential mode circulating currents," *Jun. 2022*, doi: 10.1109/EEEIC/ICPSEurope54979.2022.9854636.
 15. S. P. Jena and K. C. Rout, "Comparative analysis of harmonic reduction of VSI fed induction motor using SVPWM and sinusoidal PWM," May 2018, doi: 10.1109/ICOEI.2018.8553727.
 16. S. Kumar et al., "A comprehensive review of condition based prognostic maintenance (CBPM) for induction motor," *IEEE Access*, vol. 7, pp. 90690–90704, 2019, doi: 10.1109/ACCESS.2019.2926527.
 17. A. Khaledian, B. Vahidi, and M. Abedi, "Harmonic distorted load control in a microgrid," *Journal of Applied Research and Technology*, vol. 12, no. 4, pp. 792–802, Aug. 2014, doi: 10.1016/S1665-6423(14)70095-1.
 18. K. B. Kumar, A. Bhanuchandar, B. Supriya, D. Vamshy, K. Palle, and R. Sakile, "A unipolar phase disposition pulse width modulation technique for an asymmetrical multilevel inverter topology," in *Proceedings -2021 IEEE International Conference on Intelligent Systems, Smart and Green Technologies, ICISST 2021*, 2021, pp. 156–161, doi: 10.1109/ICISST52025.2021.00041.
 19. S. Mithun, B. T. Rao, A. Vijaywargiya, D. De, and N. B. Puhani, "Analysis of advanced space vector PWM techniques extended to over-modulation region for induction machine drive," *Jan. 2022*, doi: 10.1109/PESGRE52268.2022.9715960.
 20. P. Nehra and A. K. Sharma, "Analysis of single phase pulse width modulation (PWM) AC to AC step-up converter based on SC structure," in *2019 International Conference on Communication and Electronics Systems (ICCES)*, Jul. 2019, pp. 1401–1405, doi: 10.1109/ICCES45898.2019.9002575.
 21. R. Nagarajan and M. Saravanan, "Staircase multicarrier SPWM technique for nine level cascaded inverter," in *2013 International Conference on Power, Energy and Control (ICPEC)*, Feb. 2013, pp. 668–675, doi: 10.1109/ICPEC.2013.6527741.
 22. H. Patel and H. Chandwani, "Simulation and experimental verification of modified sinusoidal pulse width modulation technique for torque ripple attenuation in Brushless DC motor drive," *Engineering Science and Technology, an International Journal*, vol. 24, no. 3, pp. 671–681, Jun. 2021, doi: 10.1016/j.jestch.2020.11.003.
 23. S. Paswan, A. K. Maurya, M. Yadav, and N. Singh, "Hybrid trapezoidal modulation technique for conditioning of power quality and harmonic distortion based on D-statcom," in *2020 International Conference on Electrical and Electronics Engineering (ICE3)*, Feb. 2020, pp. 737–742, doi: 10.1109/ICE348803.2020.9122896.
 24. S. Subsingha, "A comparative study of sinusoidal PWM and third harmonic injected PWM reference signal on five level diode clamp inverter," *Energy Procedia*, vol. 89, pp. 137–148, Jun. 2016, doi: 10.1016/j.egypro.2016.05.020.
 25. S. Wang, Y. Ma, J. Wang, L. M. Tolbert, and F.

- Wang, "Variable speed drive connected motor load emulator for a multi-converter-based hardware testbed system," *IEEE Open Journal of Industry Applications*, vol. 2, pp. 337–346, 2021, doi: 10.1109/OJIA.2021.3121401. 10.11591/ijeecs.v27.i2.pp667-677.
26. Y. Wang, C. Zhao, L. Zhang, Z. Zhang, and H. Zhang, "Hybrid pulse-width-modulation-based simultaneous wireless laser information and power transfer system using PWM sampling," *Optics Communications*, vol. 515, Jul. 2022, doi: 10.1016/j.optcom.2022.128232.
 27. V. Srinath, M. M. Agarwal, and D. K. Chaturvedi, "Analysis and simulation of a single-phase seven-level inverter controlled by modified sinusoidal PWM technique," *International Journal of Modeling, Simulation, and Scientific Computing*, vol. 12, no. 4, Mar. 2021, doi: 10.1142/S1793962321500240.
 28. S. Yan, Y. Yang, S. Y. Hui, and F. Blaabjerg, "A review on direct power control of pulsewidth modulation converters," *IEEE Transactions on Power Electronics*, vol. 36, no. 10, pp. 11984–12007, Oct. 2021, doi: 10.1109/TPEL.2021.3070548.
 29. S. M. Ayob, Z. Salam, and A. Jusoh, "Trapezoidal PWM scheme for cascaded multilevel inverter," in *First International Power and Energy Conference, (PECon 2006) Proceedings*, Nov. 2006, pp. 368–372, doi: 10.1109/PECON.2006.346678.
 30. L. Wang, C.-S. Lam, and M.-C. Wong, "Total harmonic distortion (THD) estimation technique based on power concept for smart power meters," in *2019 IEEE PES Asia-Pacific Power and Energy Engineering Conference (APPEEC)*, Dec. 2019, pp. 1–6, doi: 10.1109/APPEEC45492.2019.8994639.
 31. J. Zhang et al., "Total harmonic distortion and output current optimization method of inductive power transfer system for power loss reduction," *IEEE Access*, vol. 8, pp. 4724–4736, 2020, doi: 10.1109/ACCESS.2019.2962900.
 32. Y. Siregar, W. K. Al-Azzawi, Z. Pane, U. E. Parhusip, and Suherman, "Study of harmonic distortion from variable speed drive and energy saving lamps," *Indonesian Journal of Electrical Engineering and Computer Science*, vol. 27, no. 2, pp. 667–677, Aug. 2022, doi: