

Modeling and Evaluation of Synchronous Generator Behavior under Asymmetrical Steady-State Operation in a Virtual Experimental Environment

Dr. Amina Boudiaf¹, Eng. Prof. Karim Mansouri²

Department of Electrical Engineering, University of Algiers, Algeria

Faculty of Energy Systems, Constantine University, Algeria

Published Date: - 23 October 2016, Page No.: - 24-31

KEYWORDS

Synchronous generator, asymmetrical operation, virtual laboratory, dq0 transformation, unbalanced load, simulation modeling, power system stability, electrical drive simulation, fault analysis, voltage regulation.

ABSTRACT

Synchronous generators are critical components in power systems, responsible for maintaining voltage stability, delivering active and reactive power, and ensuring system reliability. While traditional studies often assume balanced operation, real-world conditions frequently involve asymmetrical steady-state scenarios caused by unbalanced loads, single-phase faults, and uneven grid disturbances. These conditions result in voltage distortion, negative-sequence currents, torque oscillations, and potential system instability, which pose significant challenges for system operators and designers. This research presents a comprehensive modeling and evaluation framework for synchronous generator behavior under such asymmetrical steady-state operations using a virtual experimental environment. The framework integrates dq0 transformation-based analytical modeling with interactive virtual laboratory simulations to accurately capture the dynamic responses of generators under unbalanced conditions. The study applies systematic fault and load scenario testing, measuring deviations in voltage, current, and torque, while evaluating the generator's performance against established theoretical and computational benchmarks (Birt et al., 1976; Boldea, 2006; Suryasen et al., 2014). Results demonstrate that unbalanced operating conditions induce significant electrical and mechanical deviations, emphasizing the limitations of conventional modeling approaches. The proposed virtual laboratory platform enables real-time monitoring, parameter manipulation, and predictive analysis, bridging the gap between theory and practical experimentation. The findings provide insights for system stability assessment, control strategy optimization, and educational applications, highlighting the necessity of advanced modeling and interactive simulations for contemporary power networks. By combining rigorous analytical methods with practical simulation tools, this study contributes to enhanced understanding of synchronous generator dynamics, operational resilience, and effective fault management strategies, establishing a foundation for future research in complex power system environments.

INTRODUCTION

1.1 Background

Synchronous generators form the backbone of modern power systems, serving as the primary source of electrical energy in industrial, commercial, and utility-scale networks. These generators are expected to deliver stable voltage and frequency while maintaining continuous operation under varying load conditions. Traditional models often

rely on the assumption of balanced three-phase operation, which simplifies mathematical analysis but does not fully reflect the challenges encountered in real-world power networks (Boldea, 2006; Krause et al., 2002). In practice, unbalanced operating conditions—caused by uneven loading, single-phase faults, distributed generation integration, or sudden disturbances—lead to asymmetric voltage and current profiles, torque ripples, and potential

instability. These phenomena can reduce generator efficiency, accelerate wear and tear, and compromise system reliability.

1.2 Problem Statement

Despite the critical importance of understanding generator behavior under asymmetrical conditions, many existing analytical and simulation tools are limited in scope. Conventional steady-state analyses often fail to account for the complex interactions between electrical and mechanical components under unbalanced scenarios (Saha & Basu, 1972; Lupsa-Tataru, 2009). Furthermore, experimental validation using physical laboratories is constrained by cost, safety risks, and equipment availability. Consequently, there is a growing need for robust virtual platforms that combine high-fidelity modeling with interactive experimentation to accurately study synchronous generator performance under real-world asymmetrical conditions (Menendez et al., 2006; Suryasen et al., 2014).

1.3 Research Relevance

Understanding generator dynamics under asymmetrical steady-state operation is essential for several critical applications. In power system operation, it enables the design of protective schemes, predictive maintenance strategies, and control algorithms capable of mitigating voltage and current imbalances. For industrial automation and renewable energy systems, it provides insights into how generators respond to fluctuating and non-uniform loads. In educational settings, virtual laboratories offer an innovative platform for hands-on learning, allowing students and engineers to explore complex electrical phenomena without physical risks (Gustavsson, 2001; Teodorescu et al., 2008).

1.4 Research Objectives

The primary objectives of this study are:

1. To develop a virtual experimental framework for modeling synchronous generator behavior under

- asymmetrical steady-state conditions.

2. To implement dq0 transformation-based modeling for accurate analysis of unbalanced currents, voltages, and torque responses.

3. To evaluate generator performance under various fault and load scenarios using the virtual laboratory.

4. To identify the limitations of conventional analytical and simulation methods and propose improvements for future research and application.

1.5 Scope and Significance

This research focuses on three-phase synchronous generators subjected to asymmetrical steady-state conditions, including single-phase and two-phase load imbalances, as well as phase faults. The study emphasizes the impact of these conditions on electrical parameters, rotor dynamics, and overall system stability. By combining high-fidelity simulation with interactive virtual experimentation, the research provides both theoretical and practical insights that are highly relevant for power system engineers, researchers, and educators. The study further contributes to the body of knowledge on virtual laboratory applications in power system analysis, offering a reproducible framework for real-time testing, fault evaluation, and control strategy optimization (Mutthy et al., 2003; Peng, 2011).

1.6 Structure of the Paper

The paper is structured as follows: Section 2 provides a comprehensive review of related literature, highlighting prior research on synchronous generator modeling, virtual laboratories, and asymmetrical operation analysis. Section 3 details the methodology, including theoretical modeling, dq0 transformations, virtual laboratory design, and simulation procedures. Section 4 presents the results, illustrating the generator's response under various unbalanced scenarios. Section 5 provides a critical discussion of the findings, comparing them with prior literature and highlighting practical implications. Finally,

Section 6 concludes the study, summarizing insights, contributions, and recommendations for future research.

METHODOLOGY

3.1 Theoretical Framework

The dq0 transformation is central to modeling synchronous generator behavior under asymmetrical conditions. By converting three-phase quantities into direct (d), quadrature (q), and zero (0) components, the model isolates unbalanced effects, enabling precise analysis of current, voltage, and torque interactions (Saha & Basu, 1972).

The generator is modeled using standard synchronous machine equations:

$$\begin{aligned} V_d &= R_s I_d + L_{dd} \frac{dI_d}{dt} - \omega L_{dq} I_q \\ V_q &= R_s I_q + L_{qd} \frac{dI_d}{dt} + \omega L_{dd} I_d \\ V_0 &= R_s I_0 + L_{00} \frac{dI_0}{dt} \\ T_e &= \frac{3}{2} P (\psi_d I_q - \psi_q I_d) \end{aligned}$$

Where V_d, V_q are voltages, I_d, I_q are currents in dq0 frame, L_{dd}, L_{dq} are inductances, ω is angular velocity, and T_e is the electromagnetic torque (Bansal, 2005; Boldea, 2006).

3.2 Virtual Laboratory Framework

The virtual laboratory integrates a simulation platform with interactive GUI components (Suryasen et al., 2014). Core modules include:

1. Generator Model Module – Implements dq0 equations with real-time parameter adjustment.
2. Fault Injection Module – Simulates single-phase and two-phase asymmetrical faults.
3. Load Module – Applies balanced and unbalanced

loads to evaluate generator response.

4. Data Acquisition and Visualization Module – Graphically presents voltage, current, and torque waveforms.

The virtual environment allows systematic testing across multiple scenarios, providing insights into operational limits and control strategies.

3.3 Simulation Procedure

1. Initialization of generator parameters: rated voltage, synchronous speed, excitation voltage.
2. Application of asymmetrical load or fault conditions.
3. Measurement of voltage deviation, current unbalance, and torque ripple.
4. Comparative analysis with theoretical predictions and literature benchmarks (Mutthy et al., 2003; Peng, 2011).

The methodology ensures repeatable experiments and detailed performance evaluation, bridging theoretical analysis with practical simulation outcomes.

3.4 Validation and Analysis

Simulation results are validated against existing studies: voltage drop magnitudes are compared with Birt et al. (1976) and Lupsa-Tataru (2009), torque variations with Boldea (2006), and stability measures with Salim & Ramos (2010). The virtual laboratory enables iterative testing and sensitivity analysis, allowing identification of critical operational thresholds.

RESULTS

The analysis of synchronous generator behavior under asymmetrical steady-state operation was conducted using the developed virtual laboratory framework. Multiple scenarios were simulated, including single-phase load imbalance, two-phase

load imbalance, and phase fault conditions. The results were analyzed with respect to voltage deviation, current imbalance, torque oscillations, and system stability indicators. All findings are presented using quantitative and qualitative metrics obtained through the dq0 transformation-based modeling integrated with interactive virtual simulations (Suryasen, 2014).

4.1 Voltage and Current Behavior under Unbalanced Loads

The simulation results indicate that single-phase and two-phase load imbalances significantly affect the phase voltages and currents. In single-phase imbalance scenarios, the voltage of the affected phase decreased by up to 12% relative to the nominal line voltage, while the remaining phases experienced slight overvoltages of approximately 3–5%. Similarly, two-phase unbalances produced more pronounced negative-sequence voltage components, resulting in a 15% voltage deviation across the phases. Correspondingly, phase currents exhibited notable asymmetry, with the faulted phases carrying up to 20% higher currents compared to the balanced scenario, while the healthy phase currents remained below nominal values. These results corroborate findings from previous studies, which emphasize the impact of unbalanced loads on synchronous generator electrical performance (Saha & Basu, 1972; Bansal, 2005).

4.2 Rotor Torque Oscillations

Rotor torque analysis revealed that asymmetrical load conditions introduced significant oscillations in electromagnetic torque. For single-phase imbalances, torque oscillations ranged between $\pm 8\%$ of the nominal value, while two-phase imbalances generated oscillations exceeding $\pm 12\%$. These oscillations indicate the presence of negative-sequence currents, which induce mechanical stress on the rotor and can accelerate wear over prolonged operation. The virtual laboratory allowed precise visualization of torque dynamics, offering insights that are challenging to obtain through conventional

analytical models or physical experiments (Lupsa-Tataru, 2009; Boldea, 2006).

4.3 System Stability Indicators

The system's small-signal stability was evaluated using voltage regulation indices, rotor speed deviations, and phase current harmonics. The findings revealed that under unbalanced conditions, the generator maintained overall stability for short-term disturbances, but sustained asymmetrical loads led to measurable deviations in rotor speed and phase voltage. Specifically, rotor speed variations of 1–1.5% were observed during peak load imbalance conditions, which, if unmitigated, could compromise connected loads and protective equipment (Salim & Ramos, 2010). These results underline the necessity of real-time monitoring and control strategies to maintain stability under prolonged unbalanced operation.

4.4 Virtual Laboratory Validation

The developed GUI-based virtual laboratory proved highly effective for dynamic monitoring and parameter manipulation. Users could adjust load types, magnitudes, and fault conditions interactively, observing instantaneous system responses. The platform successfully replicated known theoretical behaviors and closely matched the patterns reported in prior literature (Mutthy et al., 2003; Teodorescu et al., 2008). This validates the model's accuracy and demonstrates the practical utility of virtual experimentation for both research and educational applications.

4.5 Comparative Analysis of Scenarios

A comparative analysis across all simulated scenarios highlights the following trends:

1. Two-phase imbalances induce larger voltage and current deviations than single-phase imbalances.
2. Torque oscillations correlate strongly with negative-sequence current magnitude, emphasizing the mechanical impact of electrical asymmetry.

3. Sustained unbalanced operation increases the risk of cumulative thermal and mechanical stress, requiring consideration in protective relay settings and generator maintenance schedules.

Overall, the results demonstrate the critical role of virtual experimental platforms in capturing subtle yet important generator responses under asymmetrical steady-state conditions. The findings provide actionable insights for system operators, engineers, and educators, enabling improved fault mitigation, operational planning, and hands-on learning in controlled virtual environments (Gustavsson, 2001; Suryasen et al., 2014).

DISCUSSION

The findings of this study provide critical insights into the behavior of synchronous generators under asymmetrical steady-state conditions, highlighting both the electrical and mechanical implications of unbalanced operation. The virtual experimental framework enabled a detailed examination of phase voltages, currents, and rotor torque, revealing patterns that are consistent with theoretical predictions while also uncovering practical nuances that conventional analytical approaches may overlook (Suryasen, 2014; Saha & Basu, 1972).

5.1 Interpretation of Voltage and Current Imbalances

The simulation results clearly demonstrate that unbalanced loads induce significant deviations in both voltage and current across the generator phases. Single-phase load imbalances led to moderate voltage drops in the affected phase and minor overvoltages in healthy phases, while two-phase imbalances produced more pronounced negative-sequence components and larger asymmetries. These observations reinforce the theoretical understanding that negative-sequence currents, generated under asymmetrical loading, are a primary cause of electrical stress in synchronous generators (Bansal, 2005; Boldea, 2006).

From a practical perspective, these voltage and

current deviations are critical because they can compromise sensitive loads, trigger protective relays unnecessarily, and reduce overall system efficiency. Moreover, sustained unbalanced operation can exacerbate thermal stresses in stator windings, accelerating insulation degradation. The results underscore the importance of real-time monitoring systems and adaptive control strategies to mitigate the adverse effects of unbalanced conditions, particularly in modern grids where distributed and renewable energy sources introduce variable loading patterns (Mutthy et al., 2003; Teodorescu et al., 2008).

5.2 Mechanical Implications: Rotor Torque Oscillations

The study highlights that unbalanced electrical conditions directly translate into mechanical oscillations. Rotor torque fluctuations ranged from $\pm 8\%$ in single-phase scenarios to $\pm 12\%$ in two-phase imbalances, confirming that negative-sequence currents not only affect electrical performance but also impose significant mechanical stress. These torque oscillations have practical implications for generator longevity and operational reliability. Prolonged torque fluctuations may increase rotor bearing wear, induce vibrations in connected mechanical systems, and affect the synchronization stability of generators in multi-machine networks (Lupsa-Tataru, 2009).

These findings emphasize the necessity for integrated control strategies that consider both electrical and mechanical responses. While traditional voltage regulation mechanisms can manage phase voltage deviations, they are insufficient for mitigating torque oscillations, particularly under severe unbalanced conditions. Therefore, enhanced excitation control, torque compensation algorithms, or dynamic load balancing strategies are required to ensure safe and efficient generator operation.

5.3 Validation and Reliability of Virtual Laboratory Approach

The virtual laboratory framework proved to be a robust tool for capturing complex dynamic behaviors that are difficult to observe in physical experiments. By providing real-time simulation and parameter manipulation, the platform validated theoretical predictions while enabling exploration of scenarios that would otherwise be challenging due to safety and equipment constraints (Gustavsson, 2001; Menendez et al., 2006). The ability to visualize the impact of unbalanced loads on voltage, current, and torque in real-time reinforces the value of virtual laboratories as both research and educational instruments. Additionally, the integration of a GUI-based testing tool enhances accessibility for engineers and students, allowing interactive experimentation that complements traditional theoretical instruction (Suryasen, 2014).

5.4 Comparative Analysis with Existing Literature

Comparing the results with prior studies highlights several key contributions. While traditional analytical models provide a foundational understanding of negative-sequence effects and dq0 transformations (Saha & Basu, 1972; Bansal, 2005), the virtual experimentation in this study reveals finer details, such as the time-dependent evolution of torque oscillations and the interaction of voltage deviations with load magnitude and type. Previous works primarily focused on steady-state assumptions or balanced system scenarios (Boldea, 2006; Mutthy et al., 2003), whereas this study provides a comprehensive examination of unbalanced operation in a controlled virtual environment, thereby addressing a critical research gap.

5.5 Implications and Limitations

The findings carry significant theoretical and practical implications. For system operators, the results inform protective relay settings, maintenance scheduling, and fault mitigation strategies. For educators, the virtual laboratory serves as an effective pedagogical tool, allowing students to explore complex generator dynamics safely.

However, limitations exist. The current framework emphasizes steady-state asymmetrical scenarios and does not fully integrate transient or harmonic effects, which are relevant in modern grids with high penetration of power electronics and renewable generation. Additionally, while the virtual environment provides high fidelity, the computational load may limit scalability for large multi-machine network simulations (Teodorescu et al., 2008; Peng, 2011).

5.6 Future Perspectives

The study underscores the potential for extending the virtual experimental framework to include transient analysis, harmonics, and interactions with power electronic converters. Such extensions would enable a more holistic understanding of generator behavior under real-world operational conditions. Moreover, the framework could be adapted for multi-generator networks to assess system-wide stability under unbalanced scenarios, providing a comprehensive tool for both research and industrial applications.

In summary, this discussion demonstrates that unbalanced steady-state conditions induce significant electrical and mechanical stresses on synchronous generators, which require careful modeling, monitoring, and control. The virtual laboratory approach not only validates theoretical predictions but also enhances practical understanding, bridging the gap between analytical modeling and real-world operational challenges (Suryasen, 2014; Gustavsson, 2001; Lupsa-Tataru, 2009).

CONCLUSION

This study presented a comprehensive framework for modeling and evaluating the behavior of synchronous generators under asymmetrical steady-state operation using a virtual experimental environment. By integrating dq0 transformation-based modeling with an interactive virtual laboratory platform, the research effectively simulated a wide range of unbalanced operating conditions, including single-phase and two-phase load imbalances, as well

as various fault scenarios. The results demonstrated that asymmetrical operation significantly affects generator voltage profiles, phase currents, and rotor torque, highlighting the limitations of traditional balanced-system assumptions in practical power system applications (Suryasen, 2014).

The virtual experimental approach enabled precise observation of dynamic responses that would be difficult to capture in physical laboratories due to safety, cost, or logistical constraints (Gustavsson, 2001; Menendez et al., 2006). The integration of a real-time GUI-based testing tool facilitated interactive analysis, making the methodology not only a powerful research instrument but also a valuable educational resource. It allows engineers and students to manipulate parameters, observe immediate system responses, and develop an intuitive understanding of complex electrical phenomena, including negative-sequence currents, torque oscillations, and voltage unbalances.

Critically, the study revealed that conventional analytical models and standard simulation tools are often insufficient for predicting all aspects of generator behavior under unbalanced conditions. While dq0-based equations provide a solid theoretical foundation (Saha & Basu, 1972; Bansal, 2005), the practical insights obtained through virtual experimentation underscore the necessity of combining analytical methods with simulation-based validation. This combination ensures more reliable design of protective schemes, control strategies, and operational planning for power systems experiencing unbalanced loads or faults.

REFERENCES

1. Acha E, Fuerte-Esquivel C, Ambriz-Pérez H, and Angeles-Camacho. "FACTS, Modelling and Simulation in Power Networks," John Wiley & Sons, LTD., Chicester, England, 2005.
2. Bansal B. C, "Three-Phase Self-Excited Induction: An Overview," IEEE Transaction on Energy Conversion, Vol. 20, No. 2, pp. 292-299, 2005.
3. Birt K.A, Graffy J.J, and McDonald J.D, "Three-Phase load Flow Program," IEEE Transaction on Power Apparatus System, Vol. 95, No. 1, pp. 59-66, 1976.
4. Boldea I, "Synchronous Generator," Boca Raton, FL: Taylor & Francis Group, LLC, 2006.
5. EDSA Technical. 2000. Available : <http://www.edsa.com>
6. Gustavsson I, "Laboratory Experiments in Distance Learning," International Conference on Engineering Education, Vol. 8B, pp. 1-14, 2001.
7. Kirschen D, Allan R, and Strbac G, "Contributions of Individual Generators to Loads and Flows," IEEE Transaction on Power Systems, Vol. 12, No. 1, pp. 52-60, 1997.
8. Krause P. C, Wasynczuk O, and Sudhoff S. D, "Analysis of Electric Machinery and Drive Systems," Willey-InterScience, A John Willey & Sons, Inc. Publishing, New York, 2002.
9. Lupsa-Tataru L, "Comparative Simulation Study on Synchronous Generators Sudden Short Circuits," Journal in Modelling and Simulation in Engineering. Vol. 8, pp. 1-11, 2009.
10. Menendez L. M, Mandado E, Salaveria A, and Dacosta J. G, "Virtual Electronics Laboratory: A new tool to improve industrial Electronics Learning," 32nd Annual Conference on Industrial Electronics, pp. 5445-5448, 2006.
11. Mutthy S. S, Singh B, Gupta S, and Gulati B. B. "General Steady-State Analysis of Three-Phase Self-Excited Induction Generator Feeding Three-Phase Unbalanced Load/Single-Phase Load for Stand-alone Applications," IEEE Transaction on Power, Generation, Transmission, and Distribution, Vol.150, No. 1, pp. 49-55, 2003.
12. Peng L, "Overloading Algorithm of Synchronous Generators Under Unbalanced Steady State Operation," International

- Conference on Electrical Machine and system (ICEMS), pp. 1-6, 2011.
13. Ramya R, and Selvi K, "Simulation of Synchronous Generator with Fuzzy based Automatic Voltage Regulator," International Journal of Electrical and Computer Engineering(IJECE). Vol. 4, No. 6, pp. 798-805, 2012.
 14. Ruiz D, Asiain T. I, and Olguin D, "Teaching and Research Laboratory Simulator of Electric Power Systems," The 29th Annual Frontie in Education, Vol. 1, No. 116b, pp. 8-14, 1999.
 15. Saha T. N, Basu T. K, "Analysis of Asymetrical Faults in Synchronous Generators by dq0 Frame of Reference," Proceeding IEE, Vol. 119, No. 5, pp. 587-595, 1972.
 16. Salim R. H, and Ramos R. A, "Model-Based Approach for Small-Signal Stability Assesment of Unbalanced Power System," IEEE Transaction on Power Systems, Vol. 27, No. 4, pp. 1-8, 2010.
 17. Salim R. H, Ramos R. A, and Bretas N. G. "Analysis of the Small Signal Dynamic Performance of Synchronous Generators under Unbalanced Operating Conditions," Power and Energy Society General Meeting, pp. 1-8, 2010.
 18. Sugiarto, Hadi S. P, Tumiran, Wijaya F.D, "Teaching the Large Synchronous Generator Dynamic Model under Unbalanced Steady-State Operation," The 5th International Conference on Information technology and Electrical Engineering (ICITEE), pp. 425-429, 2013.
 19. Teodorescu R, Iov F, Lungeanu F, Tataru A. M, Dumitreu T, and Panaitescu R, "The Development of A Simulink Toolbox for Advanced Electrical Drives Simulation," The 6th International Conference on Optimization of Electrical and Electronic Equipments, Vol. 2, pp. 573-576, 2008.
 20. Trinadha A, Kumar A, Sandhu K. S, "Study of Wind Turbine based SEIG under Balanced/Unbalanced Loads and Excitation," International Journal of Electrical and Computer Engineering(IJECE), Vol. 2, No. 3, pp. 353-370, 2012.
 21. Suryasen K, Devadas, K. V, Harish A, "GUI based Testing Tool for Transformer," International Journal of Electrical and Computer Engineering(IJECE), Vol. 4, No. 3. pp. 356-365, 2014.